

# PROGRAMMABLE KEYPAD + REMOTE

PK-I, PKR-I



The Programmable Keypad is installed in a standard single-gang wall box using a white, Decora-style faceplate. It provides occupant control of the sound masking and paging settings in private offices and meeting rooms, or anywhere else there is a need for individual control.



## Remote Control

The keypad also features an infrared remote control receiver, enabling the user to adjust the settings using the Programmable Keypad Remote (PKR-I). This feature can be disabled in high-security applications.

## User Instructions

The Programmable Keypad is easy to use.

To activate it, press any key. If the desired function is not currently highlighted, press the Select key to choose either Masking or Paging. The screen displays the current setting for that function.

To increase or decrease the volume, press the + or - key. To mute the function, press the Mute key. The screen displays two dashes. To un-mute, press the Mute key again.

To change the paging channel, press the Select key until the screen displays a C. To move to another channel, press the + or - key.



## SPECIFICATIONS

### Control Performance

Masking and paging volume control, masking and paging mute, paging channel selection, remote control receiver enable/disable

### Masking Performance

Volume Adjustment Range 99 step range in 0.5 dBA steps + mute  
Volume Restriction Administrator defines minimum and maximum  
Function Restriction Administrator enables or disables functions

### Paging Performance

Volume Adjustment Range 99 step range in 0.5 dBA steps + mute  
Volume Restriction Administrator defines minimum and maximum  
Function Restriction Administrator enables or disables functions  
Paging Channel Selection Zone 1, 2, 3 or none

### Connections

Network In/Out 6-pin

### Power

Input 30 VDC  
Consumption Maximum 6 W

### Zoning

Method Electronically zoned using Network Control Panel or Acoustic Network Manager Software  
Zone Size No limit

### Physical Specifications

Dimensions (W x H x D) 4 x 10.4 x 4.6 cm; 1.58 x 4.1 x 1.825 inches  
Color White  
Weight 120 g; 4.2 oz  
Display 2-digit LED  
Keypad 4-key membrane panel

### Remote Control

Remote Receiver Infrared remote control receiver for use with PKR-I  
Function Restriction Administrator enables or disables function

### Mounting

Single-gang wall box with white, Decora-style faceplate

### Security

Function Restrictions See restrictions noted above

### Warranty

5 years: see LogiSon® Product Warranty for details

### Certifications

Meets UL, CE, ACMA (C-Tick) and FCC standards; RoHS compliant